

Running lamp set BLS-10 LED

The running lamp set is a signalling device for guiding traffic in crosswise as well as lengthwise closures of **up to 65m** when using the running lamp set with a **cable of 10m**, or alternatively of **up to 100m** when using the running lamp set with a **cable of 14m**.

It is possible to assemble a set of 3 to 10 lamps, the running lamps are always connected into the previous lamp creating a series of lamps.

In one running lamp set, running lamps have to be used with a corresponding cable length only.



MASTER LAMP RLS-10 LED

- > **LED lamp** ø200mm **EN 12352 L8H**
- > the master lamp includes electronics, which **control up to 9 running lamps**, so that they get switched on and off from the direction of the master lamp
- > at night, electronics automatically reduce luminous intensity, to provide better orientation the lamps also have a backlight
- > moreover, the electronics include reverse polarity protection and protect the battery from deep discharge
- > 5m power supply cable with battery clips
- > the lamps can be attached to a profile of ø43mm or 40x40mm



RUNNING LAMP BLS-10 LED

- > **LED lamp** ø200mm **EN 12352 L8H**
- > the lamp is connected into the previous lamp **by a 10m cable** with connector
- > the lamps can be attached to a profile of ø43mm or 40x40mm

THE SET OF 10 LED LAMPS SUPPLIED FROM BATTERY 12V/180AH KEEPS FLASHING NONSTOP FOR UP TO 40 DAYS

RUNNING LAMP BLS-14 LED

- > **LED lamp** ø200mm **EN 12352 L8H**
- > the lamp is connected into the previous lamp **by a 14m cable** with connector
- > the lamps can be attached to a profile of ø43mm or 40x40mm

Technical data for consumption in the chart refer to a set of 10 lamps.

TECHNICAL DATA

Power supply	12/24V=
Current consumption 12V=	day 0,28A night 0,1A
Average consumption 12V=	4,5Ah / 24 hours
Current consumption 24V=	day 0,15A night 0,06A
Average consumption 24V=	2,5Ah / 24 hours

PRODUCTS

Order no.	Product name	Quantity
1-105-105110	Master lamp RLS-10 LED	1 pc.
1-105-105510	Running lamp BLS-10 LED	1 pc.
1-105-105520	Running lamp BLS-14 LED	1 pc.

ACCESSORIES

Order no.	Product name	Quantity
1-220-900100	Switch for lamps SS-x	1 pc.
1-110-100100	Small lockable battery box UZA-M/M	1 pc.
1-110-100300	Robust lockable battery box UZA-V/M B	1 pc.
2-890-010020	Battery 12V/180Ah	1 pc.
2-040-015010	Delineator panel HIT-1.L arrow 60/60	1 pc.
2-040-015020	Delineator panel HIT-1.LP arrow 60/60	1 pc.
2-040-015040	Delineator panel HIT-1.PP arrow 60/60	1 pc.
2-045-090010	Adapter Z4/lamp 60/40	1 pc.
2-050-000000	Base plate HIT	1 pc.